

MG POWER DIESEL GENERATOR Cummins® powered Genset Model:MGC 304



*Drawing above for illustration purposes only

I . GENERAL DATA

Prime Power	kW/kVA	304	380
Standby Power	kW/kVA	334	418
Frequency	Hz/rpm	50	1500
Voltage	V	400	230
Current	A	548	
Connection	/	3P 4W/Y	
Rated Power Factor	/	0.8	
Open Type (L×W×H)	mm	3000×1100×1920	
Open Type(Weight)	kg	3200	
Silent Type (L×W×H)	mm	4200×1500×2100	
Silent Type(Weight)	kg	4350	



■ Available for voltages 400/230V, 480/277V, 380/220V, 440/254V, 416/240V, 220/127V, 208/120V

■ All datas based on ISO 3046, altitude 100m (328ft), barometric pressure 100kPa (29.53inHg), air temperature 25°C (77°F), relative humidity 30%.

■ Please contact with YANAN engineer for correct generator capacity selection when the load application can't meet with the standard reference.

■ YANAN diesel generators comply with standards:ISO8528,ISO14000,ISO3046,GB755,BS5000,VDE0530,IEC34-1

II. STANDARD CONFIGURATION

Engine	Cummins, including air filters, fuel filters, oil filter, starting motor and charging alternator etc.
Alternator	YANAN brushless AC alternator
Radiator	Silent Type 50°C (Open Type 40°C) , fan protective shroud
Base Frame	<p>≤550KW: base mounted fuel tank, anti-vibration pads, battery holder</p> <p>>550KW: channel steel base frame, anti-vibration pads, battery holder</p>
Circuit Breaker	<p>≤63A: Micro Circuit Breaker (MCB) >63A ≤1250A : Molded case circuit breaker(MCCB) ,</p> <p>>1250A: Air circuit breaker(ACB)</p>
Control System	DEEP SEA 6120
Start Battery	Dry charged battery, available for 6 times starts under standard condition; connection cables.
Installation Accessories	Bellow, Elbow and flange, Exhaust silencer, etc.
Documents	Electric drawing, operation & maintenance manual, certification etc.

III. OPTIONAL CONFIGURATION

Engine Accessories	<p>◇Heavy-duty air filter ◇Coolant heater ◇Lub oil heater ◇Fuel and Water Separator</p>
Alternator And Accessories	<p>◇Stamford ◇Leroy Somer ◇Marathon ◇Anti condensation heater ◇PMG</p> <p>◇High voltage _____ kV</p>
Cooling System	<p>◇50°C radiator ◇Heat exchanger + water cooling tower + External water circulation pumping system</p> <p>◇Remote horizontal water tank system</p>
Control System	<p>◇AMF ◇Parallel ◇Practical type in low temperature environment ◇Control Screen Heater</p> <p>◇Other (Comap、DEIF)</p>
Circuit Breaker	◇3/4 poles ◇Fixed/handcart type ◇Electric mechanism
Automatic Transfer Swtich	◇ATS cabinet
Start Battery	<p>◇Nickel-cadmium battery ◇Maintenance-free battery ◇Power charger and selector</p> <p>◇Charging current meter</p>
External Fuel Tank	◇500L ◇1000L ◇1500L ◇2000L ◇2500L ◇3000L ◇4000L ◇5000L
Others	_____

IV. ENGINE DATA

Engine Model	6ZTAA13-G3	Engine Power	380	kW
Aspiration	Turbocharged and Air to air aftercooled	Displacement	13	L
Type	In-line	Bore×Stroke	130X163	mm
No. of Cylinders	6	Compression Ratio	17:1	
Governor Type	Electronic Governor	Rated Speed	1500	RPM

■ Fuel System

Prime Power Fuel Consumption	76.5	L/h	Standby Power Fuel Consumption	86.9	L/h
Fuel #	ASTM D975 No.2-D or BS2869 1998 Class A1, A2		Injection System	BYC PD	

■ Lubrication System

Lub Oil Capacity	45.42	L			
Lub #	API CF-4 15W40		Max.Temperature	121	°C

■ Coolant System

Coolant Capacity	73.1	L	Max. Top Tank Temp.	102	°C
Std. Thermostat (Modulating) Range	82-94	°C	Fan Drive Method	Shaft drive	
Cooling Fan Air Flow	690	m3/min			

■ Air Intake System

Combustion Air Flow	25.5/27.6	m3/min	Maximum Air Intake Restriction	3.2	kPa
---------------------	-----------	--------	--------------------------------	-----	-----

■ Exhaust System

Exhaust Gas Flow	26.6/28.8	kg/min	Max.Back Pressure	13	kPa
Exhaust Gas Temp	≤636	°C	Exhaust Pipe Size	φ150	mm

■ Starting System

Start Mode	DC24V Electric start	Battery	2x150	Ah
------------	----------------------	---------	-------	----

V. ALTERNATOR DATA

Alternator Model	SLG314F	Rate Power	304/380	kW/kVA
PF.	0.8	Voltage	400/230	
Phase	3	Frequency	50	Hz
Connection	3P 4W/Y	Bearing	1	
Winding Pitch	2/3	Proteccion Class	IP23	
Insulation Class	H	Efficiency	92.6%	
Tel. Influence	TIF: <50	Voltage Regulation	±1.0%	
Harmonic Coefficient	THF: <2%	AVR	AS440	
Voltage Adjust Scope	≥±5%	Excitation System	Self Excited	

VI. CONTROL SYSTEM DATA

MODEL DSE6120

■ Main feature

Electronic J1939 (CAN) and nonelectronic MPU and alternator sensing engine support for diesel, gas and petrol engines all in one variant.

With a number of flexible inputs, outputs and protections, the modules can be easily adapted to suit a wide range of applications.

■ Key Function

- ▲ Utility voltage sensing
- ▲ Generator/load power monitoring (kW, kV A, kV Ar, pf)
- ▲ Generator overload protection (kW)
- ▲ Efficient power save mode
- ▲ mains and generator closed via front panel
- ▲ 4 configurable DC outputs
- ▲ 4 configurable analog./digital inputs
- ▲ 6 configurable digital inputs
- ▲ Support for 0-10 V & 4-20 mA oil pressure sensors
- ▲ Configurable staged loading outputs
- ▲ CAN, MPU and alternator speed sensing in one variant
- ▲ 3 engine maintenance alarms
- ▲ Engine speed protection
- ▲ Engine pre-heat
- ▲ Multiple date and time scheduler
- ▲ Engine idle control for starting & stopping
- ▲ Fuel pump control
- ▲ Battery voltage monitoring
- ▲ Start on low battery voltage
- ▲ Configurable remote start input
- ▲ Alternative configuration
- ▲ Alarm including common alarm, common electric and common shutdown
- ▲ LCD and LED alarm indication
- ▲ Configurable event log (50)
- ▲ Heated display option available



DSE6120 MKIII

☆ *For more information, please visit the [official website](#).*

VII. WARRANTY POLICY

1. Guarantee for one year or 1000 hours (accord to whichever reach first) from ex-factory date. Refer to 《YANAN Diesel Generator Warranty Manual》 for more details.
2. Wearing parts(filters), incorrect man-made operation, maintenance failures are excluded from the warranty policy

VIII. DRAWING (for illustration purposes only)

